

Smart Breaker Instruction

Parameters

- Product: Smart Breaker
- Rated Voltage: AC 90-250V
- Rated Current: 10A(Max.)
- AC Frequency: 50-60Hz
- Max.Power: 2200W for 220V, 1100W for 110V

Installation method

Neutral

Line

Input

Output

On/Off Button
Press Long Time
Restore to Factory
Settings.

The power must be disconnected, pay attention to safety

Part1:Download & Registration

Scan the QR code to download " SmartLife " app from APP Store or Google Play.

Enter the register/login interface, input the phone number for getting verification code to register or through other methods at the bottom of page connecting to related authorization interface to log in.

Note: Our APP only supports 2.4GHz Wi-Fi network.

A square QR code with a central logo featuring a blue house icon inside a white circle, surrounded by a black border. The QR code is used for downloading the SmartLife app.

Part2:Easy Mode(Recommend)

Preparation:Device has connected with electricity, long press on/off button for 5 seconds until indicator light quickly flashes,the application already stepped into "Devices" interface.

- Phone has connected to WiFi router and been able to connected to Internet.
- Tap the icon "+" of the top right corner of "Devices"
- Make sure the indicator light is flashing quickly, then tap the related button in application.
- Choose the local WiFi and enter the correct password, tap "Next".
- Wait for configuring successfully, then tap "Done"


Part3:AP Mode

If failed in EZ mode, automatically skip to AP mode, or tap the icon "A" at the top right corner of "Devices", enter into "Add Device", tap "AP mode" at the top right corner.

- Long press on/off button until indicator light slowly flashes, then tap the related button in application, enter into another interface, tap "Next".
- Tap "Connect now", choose WiFi hotspot named "SmartLife-XXXX", then back to "SmartLife" application.
- Wait for configuring successfully, then tap "Done".
- Users could rename the device through tapping the icon in the middle of interface.

Part4:Profile

Profile is the entrance for the users to manage personal information,mainly show the following information(see chart):



The screenshot shows a web interface for a user profile. At the top, there are two tabs: 'Profile' (active) and 'Settings'. Below the tabs is a user profile card with a profile picture icon and the name 'Shan LIU'. To the left of the main content area is a sidebar menu with the following items: Home, Basic Setting, My Account Center, My Basic Information, Experience Center, My Skills, Feedback, and About. The main content area is currently empty.

Notice

- Please check if there is damage caused by transportation, if yes, please contact supplier for replacement.
- Please follow the specification instruction and notice to keep products in a good and safe use condition.
- Put the Smart breaker in proper condition and out of reach of the children.
- Plug in fully to the socket while using.
- The total power of being electric connected appliances could not be bigger than the maximum power of the socket.
- Do Smart breaker disassemble or install the socket, otherwise there may cause security risks.

Using Amazon Echo Quick Guide

Preparation

- Amazon Alexa APP
- Amazon Alexa account (users need to register their own account)
- Our Smart APP
- Our Smart APP account (users need to register their own account, select region as "The United States")
- Echo, Echo Dot, Tap and other Amazon voice-operated devices
- Our smart device (for example, Smart Socket)

Rename the device after configuring successfully. The name of the device is recommended to use easy pronunciation of the English words.

Set your Echo speaker by Alexa APP


- Sign in with Alexa account & password. (If not registered, sign up first.) After login, click the menu at the top left, then click 'Settings', and choose 'Set up new device'.
- Choose a device (for example, Echo). When the light page appears, long press the small dot on your Echo device until the light turns to be yellow. Then click 'Continue' on App.

Note: At this time the mobile phone can not open a variety of VPN software)

- Choose users' wifi and wait for a few minutes.
- After an introduction video, click next step. It will go to "Home" page automatically. Now the Echo is connected to Alexa APP through WIFI successfully .

Enable Our Skill in Alexa APP

- Choose "Skills" in the options bar, and then search " SmartLife " in the input box>Select " SmartLife " in the search results, and then click "Enable Skill".
(Note! There are more than one test, there will be the interface on the right, which indicates that the account has been bound. You can click on the "Disable Skill" to remove the binding, and then click on the "Enable Skill" to continue to bind a new SmartLife account.)
- Input the user name and password that you had previously registered (Only support the account in the United States);When you see the right page, it means the Alexa account is linked with SmartLife account.



The screenshot shows the Alexa app interface. At the top, it says 'Alexa Home' with a plus icon. Below that is the 'amazon alexa' logo. A green banner states 'Alexa has been successfully linked with SmartLife.' Below the banner, a message says 'You can now close this window, return to your SmartLife app, and go to the 'Discover' page to find your new devices.'

Enable Our Skill in Alexa APP

After the previous operation is successful, you can control the socket via Echo.

- Discover devices : Firstly, users need to say to Echo: "Echo, (or Alexa), Discover my devices." Echo will start to finding the devices which is added in SmartLife APP. It will take about 20 seconds to show the result. Or click "Discover devices" in Alexa APP. It will show the devices that found successfully.



The screenshot shows the Alexa app interface. At the top, there's a header with 'Smart Home' and a search icon. Below it, there's a section 'Your Groups' with a sub-header 'Add group. You can create a group of smart devices.' and a 'Create group' button. The main section is 'Your Devices' with a sub-header 'Show all the Alexa for SmartLife skill on 1/2/2018.' and a 'Discover more devices' button. There are two device cards: 'Go Office' and 'Go Home'. Each card shows a device icon, name, and a 'Test' button. The 'Go Office' card also shows '100%' and '100%' below the name.

Note: "Echo" is one of the wake-up name, which can be any of these three names (Settings): Alexa/Echo/Amazon

- Support Skill List
User can control devices by instructions like below:
Alexa, turn on [bedroom socket]
Alexa, turn off [bedroom socket]
Note: The name of the device must be consistent with the addition of SmartLife app.

